



PRODUCT NUMBER: 1010929 **Thunder T2s Headband** Earmuff

Learn more about our products at howardleight.com

Learn more about hearing conservation at hearforever.org >



Overview

Reference Number 1010929

Product Type Hearing Protection

Range Earmuffs

Line Noise Blocking Earmuffs

Brand Howard Leight by Honeywell

Brand formerly known as BILSOM

Industry

- Industry
 Administration
 Agriculture
 Army Defence
 ATEX environment
- Automotive and Part Manufacturer
 Aviation
 Building and Construction
 Catering
 - Food Industries
- Chemical Industries
 Energy or Electricity
 Fire Protection brigades
 Fishing
- Foundry
 Glass Industries
 Green Spaces
 Homeland defense
 Industrial Cleaning
- Iron and steel industry
 Laboratory
 Logistics
 Maintenance
 Medical and Pharmaceutical
- Metal steel
 Minning and Quarrying
 Offshore
 Paper Industries
 Petro-chemical
- Printing Industries
 Services
 Ship Building
 Telecoms
 Textile Industries
 Transportation
- Wood Industries Utilities
 Water treatment
 Welding

Product Use

Noise Blocking Earmuff

Features & Benefits

Feature

AIR FLOW CONTROL™ TECHNOLOGY Bilsom's patented Air Flow Control™ technology delivers optimal attenuation across all frequencies, without increasing earcup size or weight. A patented baseplate chamber and high-tech non-woven layer manage the flow of air inside the earmuff to control how sound reaches the ear. The result is better, more consistent overall attenuation for virtually all industrial noise environments. Air Flow Control is a standard feature on all Thunder series earmuffs. DIELECTRIC/PLASTIC CONSTRUCTION Thunder's robust nondeforming dielectric

Thunder T2s Headband Earmuff - 1010929

construction withstands use and abuse, while protecting your workers in electrical environments. NON-DEFORMING OUTER HEADBAND Thunder's non-deforming outer headband provides better comfort, minimizes pressure on head, withstanding rough treatment in the toughtest workplaces. INNER-VENTILATED HEADBAND Provides better positioning, minimizes pressure on the head. Soft, comfortable contact surface breathes easier in warm/humid climates. QUICK CLICK HEIGHT ADJUSTMENT Height adjustment remains fixed during wear. SNAP-IN EAR CUSHIONS Make replacement quick and easy.

Benefit

When it comes to selecting an earmuff, comfort reigns supreme with workers. That's why the Thunder series earmuff is designed with all-day comfort in mind. Headband earmuffs feature a unique dual-headband for better positioning and breathability, and non-deforming outer headband that minimizes pressure on the head. Plus, its dielectric construction withstands use and abuse, while protecting workers in electrical environments.

Technical Description

SNR (dB) 33 H (dB) 34 M (dB) 31 L (dB)

25

Attenuation Data

Frequency (Hz) Frequenz (Hz) Fréquence (Hz)	63	125	250	500	1000	2000	4000	8000
Mean Attenuation (dB) Mittlere Dämmung (dB) Atténuation moyenne (dB)	20.3	20.5	28.0	31.9	38.5	37.1	37.6	38.0
Standard Deviation (dB) Standardabweichung (dB) Déviation standard (dB)	4.2	3.6	2.8	3.5	2.7	3.4	3.1	5.2
Assumed Protection (dB) Angenommener (dB) Protection supposée (dB)	16.1	16.9	25.2	28.4	35.8	33.7	34.5	32.8

Earmuff Construction

Plastic [or Dielectric]

Other Material

POM, LDPE, PC/PBT, PP, PUR-E, PVC

Dielectric Yes

Color Black and Dark Green

Batteries Needed

NONC

Weight (grs) 231

Headband Style

Over-Head Sound Amplification

No

AM/FM Radio No

Automatic Shut-Off Function No

Audio Input Jack

....

Hi-Visibility No

Certifications

EC. Declaration of Conformity EC Category PPE 2 Quality Assurance ISO 9001 / 2000 EC Certificate Number 0401098 EC Attestation Number 200422136

Maintenance

Life Cycle

Cushions should be replaced periodically to retain maximum attenuation. Use the following as a guideline for replacement of ear cushions and insert foam. General use and wear - Ear cushions and foam inserts should be replaced at least every 6 months. Heavy use or wear in humid/extreme climates - Ear cushions and foam inserts should be replaced at least least every 3 months. Cracking or leakage is visible - replace ear cushions and foam inserts immediately.

Storage Information

When not in use, the earmuffs should be stored in a clean dry container or locker. Do not use solvents or petroleum-based products. Do not immerse the earmuffs in water.

Care Instructions

Earmuffs are an important safety product and should be inspected regularly. Its use, care and maintenance are critical to its effective performance. Earmuffs and in particular ear cushions may deteriorate with use and should be examined at frequent intervals for cracking and leakage. If the ear cushions become hard, damaged or deteriorated, they should be replaced promptly using recommended Hygiene Kits. Earmuffs should be maintained by regular cleaning. Use a mild disinfectant solution. A gentle wipe is all that is required.

Parts & Accessories

Accessories

Hygiene Kit - Packed in a plastic bag, including two ear cushions and two foam pads. Ref. # 1010975 for T2, T2H Beltclip - For carrying purpose. Old Ref. # 1000252 New Ref. # 1016730 Cool II Pads - Sweat absorbing pads. Ref. # 1000365 5-pair, Ref. # 1000364 100-pair Optisorb - cotton sleeve slides over earcup. Ref. # 3302101 Polar Hood - Ref. # 1016870 Lg/XLg; Ref. # 1016871 Sm/Med

Packaging

EAN Code 7312550109298

© Honeywell International Inc.